

WSP403 ZigBee Smart Plug

Quick Start Guide

Safety Notice


WARNING: Failure to follow these safety notices could result in fire, electric shock, other injuries, or damage to the Smart Switch and other property. Read all the safety notices below before using the Smart Plug.

- Avoid high humidity or extreme temperatures.
- Avoid long exposure to direct sunlight or strong ultraviolet light.
- Do not drop or expose the unit to intense vibration.
- Do not disassemble or try to repair the unit .
- Do not expose the unit or its accessories to flammable liquids, gases or other explosives.
- Do not use harsh chemicals or strong detergents to clean it.
- Do not place it where infants and young children can touch, children should use under parental supervision.
- Do not touch it when powering on to ensure your safety.
- Indoor use only.

Technical Specifications

Wireless connectivity	• ZigBee 2.4GHz IEEE 802.15.4
RF Characteristics	• Operating frequency: 2.4GHz • Internal PCB Antenna • Range outdoor: 100m (Open area)
ZigBee Profile	• ZigBee 3.0
Operating Voltage	• AC 100 ~ 240V 50/60Hz
Operating Power	• Max current: 10A • Standby: < 0.5W
Calibrated Metering Accuracy	• $\leq 100W$ (smaller than $\pm 2W$) • $> 100W$ (smaller than $\pm 2\%$)
Dimension	• 102 (L) x 64(W) x 38 (H) mm
Weight	• 125g

1 Introduction




The WSP403 ZigBee Smart Plug allows you to remotely control your home appliances and set schedules to automate via mobile phone. It also helps users to monitor the energy consumption remotely.

This guide will provide you with an overview of the product and help you get through the initial setup.

Make sure your appliance is within the 10A output rating of the Smart Plug.

2 Get to know your device



Reset Button

On/Off button & LED indicator

Available sockets



AU



EU



FR



UK



IT



ZA

On/Off Button. Used to switch the socket ON and OFF.

Reset Button

- **Pair mode.** Press and hold the Reset button for about three seconds until the LED indicator flashes three times, then it will continue flashing for one minute. Then, you can bind the Smart Plug with another device.
- **Reset.** Press and hold the Reset button for ten seconds (The LED indicator will flash three times at three seconds, and flash again three times at ten seconds). The indicator will keep flashing when the device is returned to default factory setting.

LED Indicator

The LED status gives the following information:

LED status	What it means
LED Flashing	The device has not joined a network or it is in pairing mode
Green LED	The power supply is ON
Red LED	The power supply is OFF
LED flashing three times	Enter pairing mode or returning to default factory setting

3

Get started

3.1 To get started, you will need:

A ZigBee Gateway

A mobile app

3.2 Connect to the gateway's network

1. Set your gateway to permit joining.

2. Plug in the smart plug and the LED indicator will start flashing.

Tip: If the indicator is not flashing, please reset the smart plug to default factory setting.

3. The smart plug will join the gateway automatically and the LED indicator will become steady when successfully joined.

Note: If the smart plug fails to join the gateway's network within one minute, simply reset the smart plug and retry.